



Heavy duty transformer terminals - bell mouth entry.

Key features.

- Manufactured from seamless copper tube to BS EN 12449: 1999
- Standard hole size of 8mm
- The 4 hole stud fixing ensures compatibility with most transformer fixing arrangements

Specification.

Material:
Seamless copper tube to
BS EN 12449: 1999

Approvals:
BS EN 61238-1-2003 and BS 4579

Cable size mm ²	Part no.	Stud size mm	B	D	Pack quantity
70	TF70	8.0	35.0	25.0	1
95	TF95	8.0	35.0	25.0	1
120	TF120	8.0	35.0	25.0	1
150	TF150	8.0	35.0	25.0	1
185	TF185	8.0	35.0	25.0	1
240	TF240	8.0	35.0	25.0	1
300	TF300	8.0	35.0	25.0	1
400	TF400	8.0	35.0	25.0	1